

UNIVERSAL Compression Connector to Cable Cross Reference Chart

Snap-N-Seal

DB Double Bubble™

CP CABLE PRO™

| 25-26 AWG CONNECTOR | | CABLE | | | |
|---|--------------------|--|--|--------------------------------------|--|
| Center Conductor: | .015 ~ .025 | Belden | Liberty | Tappan | West Penn |
| Dielectric: | .065 ~ .078 | | | | |
| Outer Jacket: | .095 ~ .110 | | | | |
| Snap-N-Seal | Double Bubble | | | | |
| FS1BNC, FS1RCA FSBNC1RGB* FSRCA1RGB* FS1BNCST* FS1RCAST* FSBNC1RA* | DB1BNCHD DB1RCA | 1277P-R, 1278P-R, 1279P-R, 1280P-R 1281R-S3-S4-S5-S6 1282R-S3-S4-S5-S6 1283S3-S5-S6 HC2648R, HC2650R | AVC-6-PLN* AVC-14-PLN* AVC-18-PLN* RGB5C-PLN* RGB5C-25-CMP | H91925 H91946 H91924 H91930 | 253CRGB 255CRGB 3CRGB 5CRGB WP258255 WP258263 WP258265 |

* = multi-piece connector for stranded or solid center conductor



| 22-24 AWG CONNECTOR | | CABLE | | | | | |
|--|--------------------|---|--|----------------|---------|-------------------------------|---|
| Center Conductor: | .015 ~ .025 | Belden | Coleman | Commscope | General | Liberty | West Penn |
| Dielectric: | .095 ~ .105 | | | | | | |
| Outer Jacket: | .145 ~ .160 | | | | | | |
| Snap-N-Seal | Double Bubble | | | | | | |
| FS15, FS15BNC FS15RCA FSBNC15RGB* FSRCA15RGB* FS15BNCST* FS15RCAST* FSBNC15RA* | DB1BNCHD DB1RCA | 1164B*, 1167B* 1371P, 13712R 1406B*, 1407B* 1417B*, 1418B* 1855A, 1855S3 1855S5, 1855S6 573945, 673948 7787A, 7788A, 7789A 7790A, 7791A, 7792A 7794A, 7796A, 8218* | 99401 99403 99405 99415 99425 99426 993211 | 7538 7538-B | 395031 | 23-YCLLSIAM RGB5C-SOL-MINI | 2825 25825 45825 825 HD25825 HD825 WP8253* WP8255* |

* = multi-piece connector for stranded or solid center conductor



| RG11 CONNECTOR | | CABLE | | | | | |
|--|---------------|--|--|-----------|----------------------------|----------------------------|------------------------------|
| Center Conductor: | .0634 ~ .0647 | Belden | Coleman | Commscope | CSC | Tappan | West Penn |
| Dielectric: | .280 ~ .294 | | | | | | |
| Outer Jacket: | .390 ~ .417 | | | | | | |
| Snap-N-Seal | | | | | | | |
| 716SNS1P11H, 716SNS1P11HQ FSNS11HBNC, FSNS11HQBNC 90SNS1P11H | | 1153A, 1523A, 1525A 1617A, 1618A, 3094A 7731A*, 8213, 9011 9064, 9764 | 821010 992153 992155 992161 991037 | 2287K | 200210 211300 211198 | C60003 C60006 C60008 | 811 821 Q821 25Q821 |

* = 7731A uses 716SNS1P11HQ or FSNS11HQBNC



CABLE PRO® INSTALLATION TOOLS

CPLCCT-SLM

CPSNSCT-596

CPLCCT-LS59/11*

CPLCRBC-BR

* = required for RG11 connectors

CABLE PRO® CABLE PREP TOOLS

| RG59 CONNECTOR | | CABLE | | | | | | | | | |
|---|--|---|-----------------------------------|------------------------------|--------------------------------------|---------------------------|--------------------------|-----------------|---------------------------------|-----------------|--|
| Center Conductor: | .0317 ~ .0339 | Belden | Coleman | Commscope | CSC | General | Genesis | Liberty | Tappan | West Penn | |
| Dielectric: | .144 ~ .157 | | | | | | | | | | |
| Outer Jacket: | .232 ~ .273 | | | | | | | | | | |
| Snap-N-Seal | Double Bubble | | | | | | | | | | |
| FSNS59U FSNS59BNCU FSNS59RCAU FSRCA59URA | FS59BNCUS FS59RCAUS FS59IECUF FS59IECUM | 1186A, 1505A 1505A-S3-S5-S6 1505F, 8221, 8263 9100, 9104, 9104P 9110, 9167, 9244, 9259 9275, 82108, 543945 | 92074 92094 99501 993253 | 5565 F5967BVV F5995BVV | 212053 212305 211301 862730 | 395025 395030 C8028 | 5001, 5013 5052, 5301 | RG59CCS- BLK | 20RG59FM/CM 20RG59FM+18/2/CM | 2815B WP8195 | |



| RG6 CONNECTOR | | CABLE | | | | | | | | | |
|---|--|--|--|---|--|---|--|----------------------------|--|---|--|
| Center Conductor: | .0399 ~ .0418 | Belden | Coleman | Commscope | CSC | General | Genesis | Liberty | Tappan | West Penn | |
| Dielectric: | .180 ~ .193 | | | | | | | | | | |
| Outer Jacket: | .265 ~ .305 | | | | | | | | | | |
| Snap-N-Seal | Double Bubble | | | | | | | | | | |
| FSNS6U FSNS6BNCU FSNS6RCAU FSNS1P6QS | DB6U DB6BNCU DB6RCAU DB6BNCHD | 152A, 1189A*, 1190A, 1530A, 1532A 1613A, 1614A, 1694A, 1840A, 1843A 1829A, 3092A, 3093A, 3131A 533945, 5339B5, 5339G5, 5339W5 5399B5, 6339Q8, 7710A, 7711A 7712A, 7713A, 7915A, 7916A 7916AP, 9058, 9062, 9066, 9077 9116, 9116R, 9118, 9248, 9290, 82120 | 92001, 92003 92008, 92041 92042, 92045 92049, 99601 192061, 192115 920036, 920414 992132, 992479 993267 | 5738 5740* F660BVV F677TSVV F6SSVV* | 200201 200206 211010 211011 211015 791224 862729 878945 | C5761 C5775 C5776 C5785 C5786 C5789 C8029 | 5002, 5003, 5007 5008, 5010, 5011 5012, 5021, 5027 5050, 5051, 5055 5060, 5061, 5066 5067, 5302, 5303 5307, 5361 | QUADFLEX* 18-CMR-SD-BLK | C40009, C40055 C40065, C40076 C40168, C40181 D40019 H90454 H90767 SU4020 SU4021 | 806 25Q841*, 2806B 6100, 6300 6310, 6350 AQC806, AQC841 AQC2806, Q841* WP6354, WP6355 | |

* = use QS connectors



Select Snap-N-Seal® ProSNS® & Double Bubble™ connectors are also available in retail packaging when ordered with [Part Number]-R.

BELDEN
SENDING ALL THE RIGHT SIGNALS®

8285 Tournament Drive
Memphis, TN 38125, USA
Customer Support: 800.685.9452
Fax: 901.748.4308
www.belden.com
cccustomerservice@belden.com

Actual cable sizes may vary from manufacturer specifications, and testing may be required to verify proper connector fit.

PLENUM Compression Connector to Cable Cross Reference Chart

Snap-N-Seal

DB Double Bubble™

CP CABLE PRO.

| RG59 SECURITY/CCTV CONNECTOR | | CABLE | | | | | | |
|------------------------------|------------------------|---|--|---------------------------|--|----------------------------------|------------------|--|
| Center Conductor: | .0317 ~ .0339 | Belden | Coleman | Commscope | General | Genesis | Tappan | West Penn |
| Dielectric: | .130 ~ .148 | | | | | | | |
| Outer Jacket: | .232 ~ .248 | | | | | | | |
| Snap-N-Seal | Double Bubble | 1426A, 8212, 8221 9240, 9265, 9659 543945, 5439W5 549945 | 92004, 92074 991055, 991057 993251, 993263 | 2054V, 5550 5553, 5554 | C1104, C1135 C1142, C8025 C8027, C8028 | 5001, 5009 5013, 5103 5104 | C30022 H90369 | 804, 814, 815 819, 2814 AQC815 AQC819 |
| FSNS59BNCSL | DB59BNCSL DB59RCASL | | | | | | | |



| RG59 PLENUM CONNECTOR | | CABLE | | | | | | | |
|--|--|---|------------------------------------|--------------------|--|---|--------------|----------------------------|--------------------------|
| Center Conductor: | .0317 ~ .0339 | Belden | Coleman | Commscope | CSC | General | Genesis | Tappan | West Penn |
| Dielectric: | .130 ~ .157 | | | | | | | | |
| Outer Jacket: | .190 ~ .220 | | | | | | | | |
| Snap-N-Seal | Double Bubble | 1370P, 1370R 1506A 8279 82259 89108 643948 649948 6439C8 | 99969 99979 993236 993256 | 2020K-V 2036K-V | 221105 221125 592002 861159 862732 | C3500 C3526 C8030 495023 495028 495044 | 5351 5355 | D30009 D30124 H90224 | 25815 25819 25Q843 |
| FSNS59PL FSNS59BNCSL FSNS59RCAPL | DB59PL2 DB59BNCSL2 DB59RCAPL2 DB59PL2/4 DB59BNCSL2/4 DB59RCAPL2/4 | | | | | | | | |



| RG59 PLENUM SIZE 3 CONNECTOR | | CABLE | |
|------------------------------|--------------------------|----------------|------------------|
| Center Conductor: | .0210 ~ .0240 | Belden | Liberty |
| Dielectric: | .130 ~ .137 | | |
| Outer Jacket: | .190 ~ .220 | | |
| Snap-N-Seal | Double Bubble | 82241 88241 | RG59-CCTV-PL-WHT |
| FSNS59BNCSL3 FSNS59RCAPL3 | DB59BNCSL3 DB59RCAPL3 | | |



| ITS CONNECTOR | | CABLE | | |
|------------------------------|-------------|---------------|---------|-----------|
| Center Conductor: | .024 ~ .034 | Belden | General | West Penn |
| Dielectric: | .190 ~ .200 | | | |
| Outer Jacket: | .295 ~ .305 | | | |
| Double Bubble | | 8281 8281B | C5816 | P806 |
| DB59BNCSL2-M DB59BNCSL2-F | | | | |



| DBDS3BNC CONNECTOR | | CABLE | |
|----------------------|-------------|--------|------------|
| Center Conductor: | .014 ~ .020 | Belden | Comm-scope |
| Dielectric: | .070 ~ .085 | | |
| Outer Jacket: | .120 ~ .140 | | |
| Double Bubble | | 735A | 73501 |
| DBDS3BNC | | | |

| DBDS4BNC CONNECTOR | | CABLE | |
|----------------------|---------------|-----------------|------------|
| Center Conductor: | .0317 ~ .0399 | Belden | Comm-scope |
| Dielectric: | .145 ~ .155 | | |
| Outer Jacket: | .220 ~ .240 | | |
| Double Bubble | | 734D1 734D1T | 734S1 |
| DBDS4BNC | | | |

| DBDS4BNCPL CONNECTOR | | CABLE | |
|----------------------|---------------|--------|------------|
| Center Conductor: | .0317 ~ .0399 | Belden | Comm-scope |
| Dielectric: | .145 ~ .155 | | |
| Outer Jacket: | .205 ~ .240 | | |
| Double Bubble | | 734A1P | 734C1P |
| DBDS4BNCPL | | | |



| RG11 CONNECTOR | | CABLE | | | | |
|--------------------------------|---------------|--|---------|------------------|------------------|----------------|
| Center Conductor: | .0634 ~ .0647 | Belden | Coleman | CSC | Tappan | West Penn |
| Dielectric: | .274 ~ .294 | | | | | |
| Outer Jacket: | .339 ~ .355 | | | | | |
| Snap-N-Seal | | 1399P, 1399R 7732A, 9292 89289, 613948 6139B8 | 821013 | 220500 220502 | D60001 D90011 | 25811 25821 |
| 716SNS1P11HPLA FSNS11HBCPLA | | | | | | |



Select Snap-N-Seal® ProSNS® and Double Bubble™ connectors are also available in retail packaging when ordered with [Part Number]-R.

| CABLE PRO® INSTALLATION TOOLS | | CABLE PRO® CABLE PREP TOOLS | |
|-------------------------------|--------------------------|-----------------------------|--|
| Snap-N-Seal | DB Double Bubble™ | | |
| | | | |
| CPLCCT-SLM | PSA59/6 | | |
| | | | |
| CPSNSCT-596 | PS59/6/RGB | | |
| | | | |
| CPLCRBC-BR | PS11 | | |
| | | | |
| CPLCCT-LS59/11* | | | |

* = required for RG11 connectors

| RG6 PLENUM CONNECTOR | | CABLE | | | | | | | |
|-------------------------------------|----------------------------------|--|--|--|--------------------------------------|---|--------------|--|------------------------------------|
| Center Conductor: | .0339 ~ .0418 | Belden | Coleman | Commscope | CSC | General | Genesis | Tappan | West Penn |
| Dielectric: | .165 ~ .172 | | | | | | | | |
| Outer Jacket: | .220 ~ .250 | | | | | | | | |
| Snap-N-Seal | Double Bubble | 1369P, 1369R 1530AP, 1695A 9116P 82120, 82248 87120, 89120 89248, 633938 633948, 639948 86120/633 | 921003 921005 921007 921009 921015 921017 993265 | 2275K-V 2277K-V 2279K-V F660BVR | 220400 220402 862733 862734 | C3521 C3523 C3524 C3525 C8031 495025 495035 495036 | 5352 5353 | D40012 D40018 D40045 H90061 H90794 | 25806 25841 256350 25T841 |
| FSNS6PL FSNS6BNCSL FSNS6RCAPL | DB6PL2 DB6BNCSL2 DB6RCAPL2 | | | | | | | | |

| RG6 PLENUM CONNECTOR Quad Shield | | CABLE | | | |
|--|---------------|-----------------------------------|---------|------------|-----------|
| Center Conductor: | .0339 ~ .0418 | Belden | Coleman | Comm-scope | West Penn |
| Dielectric: | .165 ~ .172 | | | | |
| Outer Jacket: | .245 ~ .275 | | | | |
| Snap-N-Seal | | 1152A 1189AP 3093A 3132A | 921019 | 2227 | 25Q841 |
| FSNS6PLQ FSNS6BNCSLQ FSNS6RCAPLQ | | | | | |



Actual cable sizes may vary from manufacturer specifications, and testing may be required to verify proper connector fit.