

Silver Machined Contacts: 2.5 mm diameter
for MC Part # 10382200 & 10382300

Part number = 1 contact,
sold in bags of 100



Complete the Installation	
Crimp Tool: 11147000	Crimp Dies: 11147100
Locator: 11147200	Removal Tool: 11171000

AWG	mm ²	Pin	Socket
20	0.5	1121300C	1121800C
18	0.75 - 1.0	1121310C	1121810C
16	1.5	1121320C	1121820C
14	2.5	1121330C	1121830C
12	4.0	1121340C	1121840C

Stamped & Formed Contacts: 2.5 mm diameter
for MC Part # 10383200 & 10383300

Part number = 1 contact, sold in bags of 100 or 1 reel



Complete the Installation			
For Contacts		For Reel	
Crimp Tool:	11147000	Crimp Dies:	20 - 16 AWG: 11153700 16 - 14 AWG: 11153800
Locator:	11147300		
Crimp Dies:		Removal Tool:	11160000
20 - 16 AWG:	11147180		
16 - 14 AWG:	11147190		

AWG	mm ²	Silver		Reel of 200	
		Pin	Socket	Pin	Socket
20 - 16	0.5 - 1.5	11201000	11205000	11208000	11209000
16 - 14	1.5 - 2.5	11202000	11206000	11208500	11209500

Silver Machined Contacts: 3.6 mm diameter
for MC Part # 10382000 & 10382100, 10399800 & 10399900

Part number = 1 contact,
sold in bags of 100



Complete the Installation			
Crimp Tool:	11147000	Locator:	11147210
Crimp Dies:		Removal Tool:	11171100
16 - 14 AWG:	11147110		
12 - 8 AWG:	11147120		

AWG	mm ²	Pin	Socket
16	1.5	1121070C	1121570C
14	2.5	1121060C	1121560C
12	4.0	1121000C	1121500C
10	6.0	1121010C	1121510C
8	10	1121020C	1121520C

Gold Stamped & Formed D-Sub Contacts: 1.0 mm
for MC Part # 10383600 & 10383700

Complete the Installation	
Crimp Tool:	Removal Tool:
11158400	11132500



AWG	mm ²	Pin	Socket
28 - 25	0.08 - 0.2	44429013	44429009
25 - 20	0.2 - 0.52	44429014	44429010

Coax Contacts
for MC Part # 10399200 & 10399300

Complete the Installation	
Crimp Tool:	Crimp Die:
11147000	11147130
Removal Tool:	
11171100	



Part number = 1 contact,
sold in bags of 100

Size	Pin	Socket
RG 58	11214200	11219200